



### PRODUCT DATA SHEET

#### KT115

##### DIGITAL MULTIMETER

- Measures AC/DC current up to 10A
- Measures AC/DC voltage up to 600V
- Diode test feature
- Capacitance test feature
- Resistance measurement
- Continuity buzzer
- Data hold memory function
- Auto and manual ranging
- Display: 4000 counts
- Sleep feature to save batteries
- Complies with IEC61010-1 CAT. III 300V/ CAT. II 600V
- Min / Max function for continuous testing

### ACCESSORIES

- Test leads
- Batteries
- Instruction Manual

### OPTIONAL

- KEW8112 Clamp adaptor for digital multimeters
- Calibration Certificate

# KT115

## Digital Multimeter

### SPECIFICATIONS

| Range        |                  | Measuring Range  | Accuracy  |
|--------------|------------------|--|---|
| DC V         | 400mV            | 0~600A<br>(5 Autoranging)<br>Input impedance approx. 10MΩ  | ±0.6% rdg ± 4dgt  |
|              | 40V              |  | ±1.0% rdg ± 4dgt  |
|              | 400V             |  |   |
|              | 600V             |  |   |
| AC A         | 400mV            | 20~399.9mV<br>Input impedance approx. 10MΩ   | ±1.6% rdg ± 4dgt (50/60Hz)<br>±2.0% rdg ± 4dgt (~400Hz) |
|              | 4V               |  | ±1.3% rdg ± 4dgt (50/60Hz)<br>±1.7% rdg ± 4dgt (~400Hz) |
|              | 40V              |  | ±1.6% rdg ± 4dgt (50/60Hz)<br>±2.0% rdg ± 4dgt (~400Hz) |
|              | 400V             |  |   |
|              | 600V             |  |   |
| DC A         | 400 μA           | 0~400mA<br>(2 Autoranging)   | ±2.0% rdg ± 4dgt  |
|              | 4000 μA          |  | ±1.0% rdg ± 4dgt  |
|              | 40 mA            | 0~400mA<br>(2 Autoranging)   |   |
|              | 400 mA           |  |   |
|              | 4 A              | 0~10mA<br>(2 Autoranging)  | ±1.6% rdg ± 4dgt  |
| DC A         | 10 A             | Allowable measurement time: 10A (15 seconds max)   |   |
|              | 400 μA           | 0~400μA<br>(2 Autoranging)   | ±2.6% rdg ± 4dgt (50/60Hz)<br>±3.0% rdg ± 4dgt (~400Hz) |
|              | 4000 μA          |  | ±2.0% rdg ± 4dgt (50/60Hz)<br>±2.4% rdg ± 4dgt (~400Hz) |
|              | 40 mA            | 0~400mA<br>(2 Autoranging)   |   |
|              | 400 mA           |  |   |
|              | 4 A              | 0~10A<br>(2 Autoranging)   | ±1.6% rdg ± 4dgt  |
| Ω            | 400Ω             | 0~40M Ω<br>(6 Autoranging)   | ±1.0% rdg ± 4dgt  |
|              | 4kΩ              |  |   |
|              | 40kΩ             |  |   |
|              | 400kΩ            |  |   |
|              | 4MΩ              |  |   |
|              | 40MΩ             |  | ±2.0% rdg ± 4dgt  |
| Capacity     | Diode check      | Test current approx. 0.4MΩ   | Unspecified   |
|              | Continuity Check | 0~400 Ω  | Buzzer beeps below about 70Ω                            |
| Frequency    | 40nF             | ~100μF (5 Autoranging)   | ±3.5% rdg ± 10dgt                                       |
|              | 400nF            |  | ±3.0% rdg ± 5dgt  |
|              | 4μF              |  | ±3.5% rdg ± 5dgt  |
|              | 40μF             |  |   |
|              | 100μF            |  |   |
| Reading Type | 5.12Hz           | ~10MHz<br>(8 Autoranging)<br>Input sensitivity:<br>~1MHz/more than 1.5V (RMS) over 1MHz/more than 2V (RMS) | ±0.1% rdg ± 5dgt  |
|              | 51.2Hz           |  |   |
|              | ~10MHz           |  |   |
|              | 512Hz            |  |   |
|              | 51.2kHz          |  |   |
|              | 512kHz           |  |   |
|              | 10MHz            |  |   |
| Reading Type | DUTY             | 0.1~99.9% (Pulse width/Pulse period)   | ±2.5% rdg ± 5dgt  |
|              | Averaging        |  |   |